

# 38 Series



**3833**



**3877**



**3822**

### Specification

Model No.	Cubid 3822	3833	3877
Case Dimensions (mm)	65.2 (H) X 210 (W) X 295 (D)	65 (H) X 210 (W) X 295 (D)	65 (H) X 210 (W) X 275 (D)
Color	Black	Black	Black   Silver
Main Board Size (mm)	Mini ITX Form Factor (170 x 170)	Mini ITX Form Factor (170 x 170)	Mini ITX Form Factor (170 x 170)
Front Port	USB X 2	USB X 2	USB X2

### Device Support

CD/DVD Device	Slim Type	Slim Type	Slim Type
HDD Device	2.5" Type	2.5" Type	2.5" Type
PCI Slots	N/A	N/A	N/A

### Internal Power Supply (DC-DC Converter)

Watts	80W (12V)   150W (19V)	80W (12V)   150W (19V)	80W (12V)   150W (19V)
Application	VIA C3 or C7 & Pentium- M System Pentium- 4 System	VIA C3 or C7 & Pentium- M System Pentium- 4 System	VIA C3 or C7 & Pentium- M System Pentium- 4 System

### External Power Supply (AC Adapter)


Watts	60W&80W (12V)   142.5(19V)	60W&80W (12V)   142.5W (19V)	60W&80W (12V)   142.5W (19V)
Application	VIA C3 or C7 & Pentium- M System Pentium- 4 System	VIA C3 or C7 & Pentium-M System Pentium- 4 System	VIA C3 or C7 & Pentium- M System Pentium- 4 System

### Function

Application	Set Top Box, Thin Client, Car Entertainment, Smart Mini PC	Set Top Box, Thin Client, Car Entertainment, Smart Mini PC	Set Top Box, Thin Client, Car Entertainment, Smart Mini PC
-------------	--	--	--



Internal Structure



VESA Bracket



Rear Side Panel



**VESA Bracket (Optional)**

### Appurtenance

- ◆ 60W AC Adapter or 80W AC Adapter(Optional) or 142.5W AC Adapter (P4 Version)
- ◆ Power Cord
- ◆ Screw Bag
- ◆ Stand
- ◆ ATX Cable (Support Intel 4PIN Cable)
- ◆ Slim CD Converter(Optional)